

# F-Link XP

Multi-Zone Expansion for F-Link 4



## Key Features

- ◆ 15 zone relay outputs
- ◆ Direct Plug & Play with F-Link 4 master unit
- ◆ Configuration software and data lead included
- ◆ Encrypted data link
- ◆ Data output for Scope CNX Paging option
- ◆ 12 to 24V dc input
- ◆ 30 Zone relay option

The ultimate add-on for the F-Link 4 fire linking system, the F-Link XP completes the picture with global alarm event notification



See next page for further details

# F-Link XP

## Multi-Zone Expansion for F-Link 4

### Specification

XP15: 15 relay contacts (NC,NO,C)  
XP30: 30 relay contacts (NC,NO,C)  
Contact rating: 1A @ 24V dc

Power In: 12-24V dc @ 1A

Current  
Standby: 9mA  
Full load, XP15: 234 mA\*  
Full load, XP30: 459 mA\*  
\*[15 mA per relay]

Data In: 9 way D type lead  
[Scope supplied]

Footprint:  
(H) 190 x (W) 335 x (D) 70 mm

Compliance:  
EMC: EN 301 489-1 V2.2.0 (2017/03)  
Safety: IEC 62368-1: 2018



F-Link 4 Master



F-Link XP



Scope Communications UK Ltd  
Quantum House  
Steamer Quay  
Totnes, Devon, TQ9 5AL  
England

Tel: +44 (0) 1803 860700  
Fax: +44 (0) 1803 863716  
Web: [www.scope-uk.com](http://www.scope-uk.com)  
Email: [sales@scope-uk.com](mailto:sales@scope-uk.com)



Connexions Paging option

### F-Link XP

- ◆ 15 switched relay outputs notify the Master Fire Panel which F-Link has gone into alarm
- ◆ Power input common with the F-Link (12-24V dc)
- ◆ Data cable included for connection to Master F-Link unit
- ◆ Included configuration software assigns each relay to an F-Link node for notifying a "Fire" (and/or "Fault") event
- ◆ Alternative configuration allows both "Fire" and "Fault" events for up to 7 nodes
- ◆ XP30 unit (30 relays) allows both "Fire" and "Fault" events for all 15 nodes
- ◆ Data output for use with Scope CNX paging option

Licensing: F-Link 4 operates on licence-free SRD frequencies in the UK  
F-Link CNX Paging option requires a Short Range Business licence  
Contact our sales team for further details